

42' Majestic Mountain Pine **Commercial Tree**

SKU: T-42-5MM

Features

- Commercial Grade
- Grow the tree year after year by adding more frames
- 5mm Wide Angle Conical LED Warm White
- 2' high strength steel concentric stacking frames.
- Innovative nesting design for compact storage when not in use
- Tree can be assembled with basic hand tools, no previous experience required.
- Lifetime technical and assembly phone support
- Natural lifelike appearance
- Crush resistant, UV-protected high-strength needles

Material Specs

Lighting: 5mm Wide Angle Conical

Number of LEDs: 42,950

Available Colors: Warm White. Pure White and Multi

LED Effect: Steady **Electrical Draw:** 35.85 Amps

Height: 42'

Diameter: 17' (without foliage) or 23' (with foliage)

Total Tree Tips: 149.650

Number of Branches: 419 3' Regular Branch

6' Top Branch 6 5' Topper: 1

Weight:

3' Regular Branch 10.7 lbs 6' Top Branch 9.16 lbs 5' Topper: 40lbs

Branch Box Size: 45" X 22" X 18"

A-P Frames, 5' Pole and 5' Topper Frame:

Branches on Last Frame:

Construction Type: Powder-coated frame designed for demanding outdoor applications

1" x .065 sq steel tubing ASTM A513 Steel Rings:

Electrical Harness: 14-gauge double strand wire with thermo jacketed 3 prong plugs

Number of Harness Outlets: 428

Shipping Weight: 5.920 lbs Shipping: Full Truck Load

Recommended Topper Size: 6' Topper

Hardware Specs

M10-1.5X100mm Bolt:
M10-1.5 Nut:
M10X22mm Washer:
M10 Plate (30mmX80mm):
Quantity 428
Quantity 428
Quantity 428
Quantity 428
Quantity 428
Quantity 428

Anchor Recommendation

*Highly recommend working with a professional installer for trees 42 feet and above.

Electrical Diagram

- One 80 ft. extension cord for the top 28 feet of the tree (to I ring)
- One 40 ft. extension cord for 30 ft. to 36 ft. (to M ring)
- One 40 ft. extension cord for 38 ft. to 42 ft. (to P ring)
- Extension cords should be dropped to the ground inside of the tree

*Please note: The tree top section should plug into two separate female plugs. Do not plug in all 9 strands to one outlet.

